



# Portable Site Transformer

Stock No. 31262  
31263  
31264

Part No. DPT1000/1B  
DPT1500/2B  
DPT3300/2B

## INSTRUCTIONS

### 1. GUARANTEE

#### 1.1 GUARANTEE

Draper tools have been carefully tested and inspected before shipment and are guaranteed to be free from defective materials and workmanship.

Should the tool develop a fault, please return the complete tool to your nearest distributor or contact Draper Tools Limited, Chandler's Ford, Eastleigh, Hampshire, SO53 1YF. England.

Telephone Sales Desk: (023) 8049 4333 or Product Helpline (023) 8049 4344.

A proof of purchase must be provided with the tool.

If upon inspection it is found that the fault occurring is due to defective materials or workmanship, repairs will be carried out free of charge. This guarantee period covering parts/labour is 12 months from the date of purchase except where tools are hired out when the guarantee period is ninety days from the date of purchase. This guarantee does not apply to normal wear and tear, nor does it cover any damage caused by misuse, careless or unsafe handling, alterations, accidents, or repairs attempted or made by any personnel other than the authorised Draper warranty repair agent.

Note: If the tool is found not to be within the terms of warranty, repairs and carriage charges will be quoted and made accordingly.

This guarantee applies in lieu of any other guarantee expressed or implied and variations of its terms are not authorised.

Your Draper guarantee is not effective unless you can produce upon request a dated receipt or invoice to verify your proof of purchase within the guarantee period.

Please note that this guarantee is an additional benefit and does not affect your statutory rights.

Draper Tools Limited.

### 2. INTRODUCTION

#### 2.1 SCOPE

Convert mains 230V to 115V for use when working on site. Two 16A sockets side by side. Double wound to class F insulation and centre tapped to earth.

#### 2.2 SPECIFICATION

Stock no	31262	31263	31264
Part no	DPT1000/1B	DPT1500/2B	DPT3300/2B
Input voltage	230V~50Hz	230V~50Hz	230V~50Hz
Output voltage	110V	110V	110V
Output amperage	16A	16A	16A
Intermittent rating	1.0kVA	1.5kVA	3.3kVA
Continuous rating	approx. 60% of int. rating	approx. 60% of int. rating	approx. 60% of int. rating
Power factor	0.93 lag	0.93 lag	0.93 lag
Waterproof	IP44	IP44	IP44
Rated max. ambient temperature	20°C	20°C	20°C
Impedance voltage	5.6%	5.6%	5.6%
No. of 16A sockets	two	two	two
Weight (approx.)	10.5kg	11kg	17.5kg

#### 2.3 HANDLING & STORAGE

Although this machine is small in size, care must still be taken when handling and lifting. Dropping this machine will have an effect on the accuracy and may also result in personal injury. This machine is not a toy and must be respected.

The environment will have a negative result on its operation if you are not careful. If the air is damp, components will rust. If the machine is unprotected from dust and debris; components will become clogged: And if not cleaned and maintained correctly or regularly the machine will not perform at its best.

### 3. HEALTH & SAFETY INFORMATION

#### 3.1 CONNECTION TO THE POWER SUPPLY

Make sure the power supply information on the machine's rating plate are compatible with the power supply you intend to connect it to.

This product comes supplied with a UK standard 3 pin plug fitted. It is designed for connection to a domestic power supply rated at 230V AC.

This transformer is a Class 1 machine; meaning, it must have an earth connection in the power supply. This is to prevent electrocution in the event of a failure.

Apart from replacing the fuse in the plug, no other electrical work is recommended on this product.

**Helpline: (023) 8049 4344. Sales Desk: (023) 8049 4333. General Enquiries: (023) 8026 6355.**

DRAPER TOOLS LTD, HURSLEY ROAD, CHANDLER'S FORD, EASTLEIGH, HANTS. SO53 1YF. U.K website: www.drapertools.com e-mail: sales@drapertools.com

KCKC250312